



461 BOSTON STREET - UNIT E6
TOPSFIELD, MA 01983
(978) 887-2020 meters@spectrumind.com

BREAKER CONTROL SWITCHES PART NUMBERING SYSTEM


APPLICATION

(REFERENCE SHALLCO CATALOG SHALLCO-SER 26 PAGES 9 - 11)

BASE PART NO.


CONTACT TABLE

2636D




DECK	CONTACTS	POS.
1	12O-II-O13	normal
	16O-II-O17	TRIP

2638D



DECK	CONTACTS	TRIP	POS.
1	11O-II-O18	X	normal
	16O-II-O17		CLOSE

2640D




DECK	CONTACTS	TRIP	POS.
1	12O-II-O13		normal
	15-16 O-II-O14	X	CLOSE

2641D



DECK	CONTACTS	TRIP	POS.
1	11-12 O-II-O18	X	normal
	15-16 O-II-O14	X	CLOSE

2642D



DECK	CONTACTS	TRIP	POS.
1	11O-II-O12	X	normal
	15-16 O-II-O14	X	CLOSE
2	22O-II-O23		normal
	26O-II-O27		CLOSE

2643D




DECK	CONTACTS	TRIP	POS.
1	12O-II-O13	X	normal
	15-16 O-II-O14		CLOSE
2	21O-II-O22	X	normal
3	32O-II-O33		CLOSE

2644D



DECK	CONTACTS	TRIP	POS.
1	11O-II-O18	X	normal
	16O-II-O17		CLOSE
2	21O-II-O22	X	normal
	25O-II-O26	X	CLOSE
3	32O-II-O33		normal
	36O-II-O37		CLOSE

2645D



DECK	CONTACTS	TRIP	POS.
1	11O-II-O18	X	normal
	16O-II-O17		CLOSE
2	21O-II-O22	X	normal
	32O-II-O33		CLOSE
3	36O-II-O37		normal
	41O-II-O42	X	CLOSE
4	45O-II-O46	X	normal
			CLOSE

BASE PART NO.

CONTACT TABLE

2646D




Diagram of the 2646D Breaker Control Switch. It features a rectangular body with a circular handle in the center. Above the handle is a switch labeled 'TRIP' and 'CLOSE'. Below the handle is a circular button labeled 'PULL TO LOCK'. The top of the unit has two terminals labeled '1' and '2'.

DECK	CONTACTS	POS.			
		TRIP	nat	nac	CLOSE
1	11O-II-O18	X			
	14O-II-O15	X			
2	21O-II-O22		X	X	
	26O-II-O27				X
3	32O-II-O33			X	X
	36O-II-O37			X	X
4	42O-II-O43			X	X
	46O-II-O47			X	X

2650D




Diagram of the 2650D Breaker Control Switch. It features a rectangular body with a circular handle in the center. Above the handle is a switch labeled 'TRIP' and 'CLOSE'. Below the handle is a circular button labeled 'PULL TO LOCK'. The top of the unit has two terminals labeled '1' and '2'.

DECK	CONTACTS	PULL-TL	POS.			
			TRIP	nat	nac	CLOSE
1	11O-II-O18	X	X			
	22O-II-O23					X
2	26O-II-O27					X
	31O-II-O35		X	X	X	X

2652D




Diagram of the 2652D Breaker Control Switch. It features a rectangular body with a circular handle in the center. Above the handle is a switch labeled 'TRIP' and 'CLOSE'. Below the handle is a circular button labeled 'PULL TO LOCK'. The top of the unit has two terminals labeled '1' and '2'.

DECK	CONTACTS	PULL-TL	POS.			
			TRIP	nat	nac	CLOSE
1	12O-II-O13					X
	16O-II-O17					X
2	21O-II-O22			X	X	
	25O-II-O26			X	X	
3	31O-II-O38	X	X			
	41O-II-O48	X	X			
4	52O-II-O53				X	X
	56O-II-O57				X	X

2657D




Diagram of the 2657D Breaker Control Switch. It features a rectangular body with a circular handle in the center. Above the handle is a switch labeled 'TRIP' and 'CLOSE'. Below the handle is a circular button labeled 'PULL TO LOCK'. The top of the unit has two terminals labeled '1' and '2'.

DECK	CONTACTS	TRIP	POS.			CLOSE
			nat	nac		
1	12O-II-O13					X
	16O-II-O17					X
2	21O-II-O28	X				
	24O-II-O25	X				
3	31O-II-O32		X	X		
	35O-II-O36		X	X		
4	42O-II-O43			X	X	
	46O-II-O47			X	X	
5	51O-II-O52	X	X			
	55O-II-O56	X	X			

2658D




Diagram of the 2658D Breaker Control Switch. It features a rectangular body with a circular handle in the center. Above the handle is a switch labeled 'TRIP' and 'CLOSE'. Below the handle is a circular button labeled 'PULL TO LOCK'. The top of the unit has two terminals labeled '1' and '2'.

DECK	CONTACTS	PULL-TL	TRIP	POS.			CLOSE
				nat	nac		
1	12O-II-O13						X
	16O-II-O17						X
2	21O-II-O28		X				
	24O-II-O25		X				
3	33O-II-O34	X					
	37O-II-O38	X					
4	41O-II-O42			X	X		
	45O-II-O46			X	X		
5	52O-II-O53				X	X	
	56O-II-O57				X	X	
6	61O-II-O62		X	X			
	65O-II-O66		X	X			

PART NO. BUILD UP SEQUENCE

LIGHTED PANEL INFORMATION
(WHEN REQUIRED)

26XXX XXXXXXXXXXXXX

BASE CONTROL SWITCH
PART NUMBER
(5 DIGITS)

VOLTAGE
5 OR 6 DIGITS

LED
POSITION
AND COLOR

MOLEX
PLUG

SEE TABLES


VOLTAGES

24VDC
(15 - 40 VDC)


125VDC
(40 - 140 VDC)

125VAC
(115 - 140 VAC)

STD COLORS
A = GREEN
B = AMBER
C = RED
D = WHITE
E = BLUE
X = NO LED



MOLEX PLUG



WP
(SUFFIX
WHEN
MOLEX
PLUG
IS NEEDED)

EXAMPLES:

2638D

BASIC BREAKER CONTROL SWITCH

2638D 125VDCABC

BASIC BREAKER CONTROL SWITCH
125 VDC LIGHTED PANEL
RED - AMBER - GREEN LED'S

2638D 24VDCAXC

BASIC BREAKER CONTROL SWITCH
24 VDC LIGHTED PANEL
RED - (NO LED) - GREEN LED'S

2638D 125VACCBWAP

BASIC BREAKER CONTROL SWITCH WITH
125 VAC LIGHTED PANEL
GREEN - AMBER - RED LED'S
WITH MOLEX WIRING PLUG

REV. B

